

# P3000I

## Compact & Lightweight



### POWERRUSH

MORE STARTING CAPACITY ALLOWING YOU TO DO MORE WITH LESS.  
POWERRUSH increases electrical current upon demand, above rated output when starting electric motors

#### Single phase power

Power LTP	kW	2.50
Power COP	kW	2.30
Voltage	V	230
Frequency	Hz	50
Power factor	cos $\phi$	1

#### Ratings definition (According to standard ISO8528 1:2005)

**COP** - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

**LTP** - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

## Engine

Type		165F-4
Displacement	cm <sup>3</sup>	149
Cylinder		1
Fuel		Petrol
Aspiration		Natural
Cooling System		Air
Starting system		Recoil

## Consumption

Consumption at 75% of load	l/h	1.14
Tank capacity	l	4
Running time at 75% COP	h	3.5

## Noise level

Acoustic power LWA	dB(A)	88
Acoustic pressure at 7m	dB(A)	61

## Dimensions and weight

Length	(L) mm	565
Width	(W) mm	339
Height	(H) mm	467
Weight (dry)	Kg	27

## Control Panel

Manual Start and Stop		•
Protection Control panel	IP	44
Economiser		•
Parallel kit receptacles		•
USB		•
Sockets	2 SCHUKO 230V 16A	

## Protection

Low oil level (oil guard)		•
Overload		•
Overvoltage		•
Overtemperature		•

## • : Standard

- : Standard



The information is aligned with the Data file at the time of download. Printed on 15/01/2021 (ID 12072)

©2021 | PR INDUSTRIAL s.r.l. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

